

Part No 43176

## **USB 3.0 HUB & GIGABIT ETHERNET CONVERTER**

## 3 PORT USB HUB & GIGABIT ETHERNET



DESCRIPTION RELATED PRODUCTS

- Connects a USB 3.0 Type A computer to a Gigabit Ethernet network
- Provides three USB 3.1 Gen 1 / 3.0 Type A ports
- Supports 10/100/1000BASE-T, full and half duplex mode
- USB 3.1 Gen 1 / 3.0 SuperSpeed data transfer rates up to 5Gbps
- 2 year warranty

The Lindy USB 3.0 Hub & Gigabit Ethernet Converter allows users to conveniently connect a notebook or ultrabook to a Gigabit Ethernet network via a Type A USB port and also provides three additional USB 3.1 Gen 1 / 3.0 Type A ports.

This converter is ideal for notebooks which do not feature wired network connectivity and may only offer a limited number of USB norts

With its small size and lightweight design this USB 3.0 Hub & Gigabit Ethernet Converter is easy and convenient to carry, and because it is powered by the USB Bus no power adapter is required.

N/A

## USB 3.0 HUB & GIGABIT ETHERNET CONVERTER



**SPECIFICATIONS** 

Interface USB to RJ45 & 3x USB Type A

USB 3.1 Gen 1 / 3.0, Gigabit LAI Interface Standard

Supported Bandwidth 5Gbps, 10/100/1000Mbps AX88179 (LAN), VL813 (Hub) Chipset

Compatibility USB Type A equipped compute

**Power Delivery** 

**CONNECTORS** 

Inputs 1 x USB Type A (Male)

Outputs 1 x RJ45 (Female), 3 x USB Type A

(Female)

Power Bus-powered

PHYSICAL PROPERTIES

**Special Features** 

40x110x20mm Dimensions (approx.) WxDxH

(1.57x4.33x0.79in)

290mm (11.42in) (Fixed) Cable Length

Plastic Housing Material

Net Weight 0.06kg (0.13lb)

0°C - 70°C (0°F - 158°F) Operating Temperature -10°C - 55°C (14°F - 131°F) Storage Temperature

10 - 90% RH (non-Humidity condensing)

Power Requirements

Black Colour

**MISCELLANEOUS** 

Packaging Type

Packaging Dimensions 175x129x30mm (6.89x5.08x1.18in)

Gross Weight 0.1kg (0.22lb)

Warranty (Years)

Certificated CE, FCC, RoHS, REACH

**PURCHASING INFORMATION** 

No. 43176

4002888431767 EAN

PACKAGING CONTENT

USB 3.0 Hub & Ethernet Converter

LINDY Driver CD LINDY Manual