



Datenblatt - Fiche technique - Data sheet

**14.99.3430**



VALUE VGA-Verlängerung via TP, max. 180m

VALUE Prolongateur VGA via TP, 180 m

VALUE VGA Extender over Twisted Pair, 180 m

# VGA EXTENDER



**(Local)**



**(Remote)**

**(14.99.3430)**

## USER MANUAL

V1.0

### Package Contents-

- VGA-L Local Unit
- VGA-R Remote Unit
- 1 user manual
- 2 power adapter DC 12V/600mA
- 1 1.2M cable (HD-15 Male to Male)

Anything missed, please contact with your vendor.

## Features

- The extension of VGA signal is up to 180 meter away by using the VGA Extender and one CAT.5 cable.
- Equalization length is adjustable.
- VGA signal gain is adjustable.

## Specifications

Function	VGA-L	VGA-R
VGA In/Out Connector	HD-15 Female x 1	
RJ-45 Connector	1	
Max. Resolution	1280x1024 60Hz	
Cable Distance	180 m (Max.)	
Power Adapter (Min.)	DC 12V 600mA	
Housing	Metal	
Weight	135g	140g
Dimensions (LxWxH)	92x34x22 mm	

### LOCAL FRONT VIEW



1. Power jack
2. Power LED
3. CAT.5 (RJ-45 Connector)

### LOCAL REAR VIEW



1. VGA In (HD-15 Female Connector)

### REMOTE FRONT VIEW



1. Power jack
2. Power LED
3. CAT.5 (RJ-45 Connector)

### REMOTE REAR VIEW



1. VGA Out (HD-15 Female Connector)

### REMOTE BOTTOM VIEW



1. EQ – Equalization length adjust (Adjust it and weak characters be sharp)
2. GAIN – Adjust brightness

## Installation

1. Turn off the PC.
2. Connect 14.99.3430 Local Unit HD-15 female connector with HD-15 male to male cable from PC.
3. Connect the 14.99.3430 Local and Remote Unit with CAT.5 cable.
4. Connect 14.99.3430 Remote Unit HD-15 female connector with HD-15 male to male cable from monitor.
5. Connect the power cord each side.
6. Turn on the monitor and PC.